

# Ultra Long-Range Receivers

## DESCRIPTION

- 1 Channel, 400 metre Line-of-Site Receiver units
- 12/24V AC/DC Input

## FEATURES

- Code-Hopping Encryption
- Selectable Latching Relay Contact
- Selectable 1 or 3 Seconds Momentary Relay Contact
- Buzzer sounds on each activation
- User friendly for programming additional transmitters
- Programmable via a Master remote
- Unit can be defaulted (memory cleared) if required



## SPECIFICATIONS

Encryption.....	Code-Hopping
Frequency available.....	403.55MHz / 433.92Mhz
Range 1m above ground.....	Indoors: +/- 250m Line-of-Site: +/- 400m
Memory Capacity.....	32 Code-Hopping Remotes
Voltage Nominal.....	12V DC
Voltage Range.....	11 - 24V AC/DC
Frequency Stability.....	0.3KHz ppm/k2
Power Consumption in use.....	10mA
Humidity.....	95% RH Maximum
Temperature.....	-20°c ~ 60°c
Dimensions.....	190 x 60 x 55mm

## SECURITY DISTRIBUTORS

is proud to introduce the [Ultra Long-Range Receiver](#) units.

Designed to be used with our Code-Hopping Transmitters, this receiver is designed with our extremely stable superheterodyne receiver circuit.

Switching applications are endless. Typically the product can be used to open & close gates, garage doors, arm & disarm Alarm systems, for Panic systems, as well as for use with Water Pump controllers for Farmers.

This Reliable Receiver has all the features and performance to suit almost any Ultra Long-Range switching application.

## Order Codes:

### RX1-400

1-Channel Receiver

### RX4-400

4-Channel Receiver

### PUMP-RX

1-Channel On/Off Receiver

Distributed by: